

S P E C I F I C A T I O N

TO ALL WHOM IT MAY CONCERN:

Be it known that I, Robert M. Fries, a citizen of the United States, residing at 16530 NE 122nd Street, Redmond, Washington 98052, have invented a certain new and useful INTERACTIVE ENTERTAINMENT AND INFORMATION SYSTEM USING TELEVISION SET-TOP BOX of which the following is a specification.

INTERACTIVE ENTERTAINMENT AND INFORMATION SYSTEM USING
TELEVISION SET-TOP BOX

CROSS-REFERENCE TO RELATED APPLICATION

5

The present application is a continuation of United States Patent Application Serial No. 08/882,908 filed June 26, 1997.

FIELD OF THE INVENTION

10

The invention relates generally to interactive television, and more particularly to an interactive entertainment and information system using a cable television set-top box.

BACKGROUND OF THE INVENTION

15

The existing network of coaxial cable television wiring was once foreseen as providing the primary high-speed infrastructure for linking computers and computerized televisions to sources of information such as the Internet. However, it is becoming apparent that the availability of such cable-based information access will not be realized in the near term, if ever, particularly as competing high-speed transmission media (such as that based on higher quality telephone lines, faster modems and ISDN technology) become entrenched. Indeed, the current economic climate has made it impractical, or at least extremely risky, for cable television service providers to replace their existing base of possibly tens or even hundreds of thousands of receive-only cable set-top converter boxes with computerized transmit-and-receive

20

25

cable modems. However, such two-way cable modems are needed to provide subscribers with interactive television and a real-time, high-speed link to information services, while simultaneously providing conventional television programming thereon.

At the same time, it is certain that many cable subscribers simply want low-cost television programming. This leaves cable providers with the dilemma of losing subscribers if they raise prices in order to upgrade their systems, or being left behind by new competitors and competing technologies if they do not. One solution is to convert to new technologies gradually. For example, conventional television programming can now be transmitted over cable in a digital format, enabling the transmission of many more (virtual) channels on the same bandwidth cable. Rather than force all subscribers to convert to the digital format, however, cable service providers will transmit a mixture of analog and digital signals for a period of time. This reduces the total number of channels transmitted to less than the maximum possible allowed by the bandwidth, but allows the cable companies to keep subscribers who are reluctant to convert.

Regarding information services on the television, a number of low-cost devices presently exist for allowing access to information services using a television set instead of a computer monitor. However, these devices do not approach

interactive television, but instead do little more than use the television display as an inexpensive monitor while connecting to the information service via a conventional, telephone-based modem. As a result, with such a device there is no direct
5 connection between programs transmitted to a viewer and interaction with web pages or the like about those programs. For example, a viewer of a home shopping channel wishing to purchase a displayed item cannot simply do so with the low cost-device, but instead must first connect to the information
10 service (e.g., the Internet) via the user's service provider, find the shopping channel's web-site (if one exists), find the appropriate item (if available on the web-site) and then place the order. Most significantly, these devices tie up a telephone line for long periods of time, a significant drawback
15 in many households.

OBJECTS AND SUMMARY OF THE INVENTION

Accordingly, it is a general object of the present invention to provide an interactive entertainment and
20 information system using a cable television set-top box.

A related object is to provide the above system using existing digital set top boxes without need for modification of the hardware therein.

Another object is to provide a system as characterized
25 above that enables a user to hyperlink between pages of information.

Yet another object is to provide a system of the above kind that facilitates an interactive relationship between transmitted programming and information pages related thereto.

A related object is to allow a user to submit form
5 information, including forms related to a viewed television program.

In accomplishing those objects, another object is to provide a simple to operate, low cost information service to those users desiring same.

10 Still another object is to provide a system of the above kind that is flexible and extensible.

Briefly, the present invention provides an interactive television system including a head-end having means for injecting video information into a transmission medium. The
15 video information includes a plurality of page images. Detection means at a subscriber end, such as hardware and software in a cable set-top box in conjunction with a remote control device, detect a first request to display one of the plurality of page images. Upon detection of the first request,
20 the box selects and displays the page image, wherein the page image includes at least one active location, such as a link, having an action corresponding thereto. The detection means further detects a second request to take the action that corresponds to the active location, whereupon the action is
25 taken. For example, a new page might be displayed when a link

is selected. The video information includes meta-data or the like associated therewith for providing information about the active location and the action to be taken upon selection thereof. Other actions may include those related to form entry
5 and submission of form data.

Other objects and advantages will become apparent from the following detailed description when taken in conjunction with the drawings, in which:

10

BRIEF DESCRIPTION OF THE DRAWINGS

FIGURE 1 is a block diagram representing a cable television system in which the present invention may be incorporated;

15

FIG. 2 is a block diagram representing a head-end of a cable television system in accordance with the present invention;

FIG. 3 is a block diagram representing a digital set-top box for receiving cable transmissions at the subscriber end of the cable television system of FIG. 1;

20

FIG. 4 is a diagram of an exemplary remote control device for providing user-commands to the digital set-top box of FIG. 3;

25

FIGS. 5A - 5B comprise a flow diagram representing the general steps taken by a browser to access an information service in accordance with one aspect of the present invention;

FIG. 6 is a representation of an exemplary page image having page elements thereon;

FIG. 7 is a flow diagram representing the general steps taken by a browser to display a page;

5 FIG. 8 is a representation of an exemplary page image having form elements thereon;

FIG. 9 is a representation of the logical organization of program elements, including page images, within programs;

FIG. 10 is a block diagram representing server components
10 for injecting page information into the cable transmission;

FIG. 11 is a flow diagram representing the general steps taken to construct a carousel of pages; and

FIG. 12 is a block diagram representing the authoring of a page for the information service.

15

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

I. OVERVIEW

A basic feature of the Information Service architecture described below is the ability to deliver a stream of MPEG
20 still images, or image pages, to a cable user (subscriber). Associated with these high-quality pages is a set of meta-data describing links to other pages along with a limited set of side effects and actions. The user can select and activate the links with a hand-held remote control, thereby interacting with
25 the pages of information displayed on the television screen.

II. THE HEAD-END

Turning to the drawings and referring first to FIG. 1, there is shown a system generally designated 20 into which the present invention may be incorporated. In general, the system
5 20 transmits signals comprising video and audio information from a cable head-end 22 onto a coaxial cable transmission medium 24, the signals being received at a plurality of subscriber locations $26_1 - 26_n$. Signal boosters (not shown) may be provided for amplifying and distributing the signals to
10 the plurality of locations. At least one of the subscriber locations, such as the location 26_1 , includes a digital set-top box 28 or the like equipped to convert the transmitted signals into signals capable of being received by a standard (e.g., NTSC) television set 30 for displaying video images and/or
15 outputting audio to a consumer end-user. Of course, the present invention does not require coaxial cable as the physical transmission medium, as signals can alternatively be transmitted over any transmission medium, including wireless means such as so-called "wireless cable" broadcasts, digital
20 satellite communication, and so on.

As shown in more detail in FIG. 2, the head-end 22 includes a head-end LAN 32, including a download server 34 and an access control server 36, for controlling the operation of the head-end 22 via an Ethernet connection 38 to the various
25 components therein. One of the components connected to the LAN

is a satellite integrated receiver/transcoder 40, which, as is known, receives and encodes digital television programming signals such as originating from microwave broadcasts received via a satellite antenna (dish) 42. One such

5 receiver/transcoder 34 is manufactured by General Instrument Corporation, Model No. IRT 1000, and outputs twenty-seven megabits per second (27Mb/s) MPEG2 transport streams modulated onto a forty-four megahertz intermediate frequency carrier. In turn, the MPEG2-encoded transport streams are received by an
10 intermediate frequency to radio frequency (IF/RF) upconverter 44, (General Instrument Corporation, Model No. C6U), which modulates the streams onto six megahertz (analog) channels and injects the signals onto the cable transmission medium 24. With multiplexing of multiple, packetized digital signals per
15 six megahertz analog channel, hundreds of digital channels may be injected onto a single coaxial medium, although at present a mixture of analog and digital channels will likely be transmitted.

According to one aspect of the invention and as described
20 in more detail below, in addition to conventional television programming, the cable head-end 22 outputs a plurality of still images, or information pages to information service subscribers. To this end, the cable head-end 22 includes an information server 46. The primary function of this head-end
25 server 46 of the Information Service is to receive and store

page data and carousel management information from content providers, and then to inject the page images onto the local cable system, i.e., produce a real-time carousel data stream for modulation onto a six megahertz channel of the transmission medium 24. The server 46 may have the page image data permanently stored therein, but typically will regularly download at least some of the page image data from an external data source 48 such as the Internet. As described below, the subscriber can interact with the digital set-top box 28 to selectively display the various page images on the screen of the television set 30.

More particularly, the information service server includes a carousel delivery application 49 for delivering a carousel 50 (FIG. 2) of rendered HTML page images to the set-top box 28 along with meta-data for each page. Each page image consists of a single frame MPEG2 video sequence that is capable of being decoded by an MPEG video decoder 52 in the set-top box 28 (FIG. 3). The meta-data for each page describe the structure and contents of the page image. As described above, the carousel 50 of page images and meta-data are delivered to a client set-top-box 28 as a standard MPEG2 Transport Stream, broadcast in-band over a six MHz NTSC channel.

The preferred head-end interactive information server 46 comprises a rack-mounted personal computer, including an Intel Corporation P6 200 megahertz (or better) central processing

unit, 128 megabytes of RAM, a two gigabyte or larger hard disk drive, and an ISDN or better connection to the external data source (Internet) 48. The server 46 also includes an Ethernet connection 38 to the local head-end LAN 32, and a TAXI (serial
5 protocol) interface card 54 (FIG. 2) along with an appropriate TAXI driver 55 therefor. The operating system is Windows NT Server 4.0. Although only one such server 46 is necessary for a typical head-end 22, two information service servers may be installed in a head-end for purposes of increased reliability
10 based on redundancy. For redundant systems, the NT Servers will run Microsoft Clustering software.

As shown in more detail in FIG. 2, to inject the signals, the information server 46 is connected via its taxi interface card 54 (on copper) to an in-band data modulator 56 connected
15 to an intermediate frequency to radio frequency upconverter 58. The preferred in-band data modulator 56 is manufactured by General Instrument Corporation, model number IM-1000, which accepts 27 Mb/s transport streams from the information service server 46 and encodes and modulates those signals to a 44 MHz
20 intermediate frequency. As with the redundant servers, there may be two IM-1000 in-band data modulators.

A second IF/RF Upconverter 58 (General Instrument Corporation, Model No. C6U) converts the 44MHz intermediate signal to an RF signal and injects the RF signal into the cable
25 system's transmission medium 24. In this manner, the 27 Mb/s

MPEG2 transport streams containing page images originating from the information server 46 are modulated onto a six megahertz analog channel for reception by subscribers.

Lastly, the head-end 22 includes an out-of-band data multiplexor 60 (General Instrument Corporation, Model No. OM-1000) which is a required component of virtually any head-end 22. As is known, the out-of-band data multiplexor 60 may be used by the present information service to communicate information service-related data to the cable network. This data, including channel maps and possibly email as described below, is routed through the cable nation data center, and is thus only indirectly related to the operation of the information service head-end 22.

15 *III. THE SUBSCRIBER END*

A. HARDWARE

Turning to the subscriber end of the system 20, as best shown in FIG. 3, the preferred set top box 28 is a digital set top box manufactured by General Instrument Corporation, Model No. DCT-1000. Although not necessary to the invention, it is significant that with this particular set-top box the hardware is unmodified, so that the existing base of publicly distributed set-top boxes may implement the Information Service without requiring upgrade servicing or replacement. However, to provide the service in accordance with the present

invention, the operation of the box 28 is modified by additional software downloaded thereto. Such software includes a browser 62 which communicates with an operating system 64 of the box 28 by placing calls through an application programming interface (API) 66, as described in more detail below.

As shown in FIG. 3, the digital cable box 28 includes an in-band tuner 70 and an out-of-band tuner 71, along with appropriate demodulators 72 and 73, respectively. A microprocessor 74 controls the tuning operation of the tuners 70 and 71 based on commands received from a subscriber via an input device such as a keypad or an infrared remote control device 76, as described below. To this end, the set-top box 28 includes an infrared sensor 78 connected to an infrared receiver 80 which provides the command signaling information to the microprocessor 74. A memory system 82 includes the VRTX operating system 64 stored therein, and preferably comprises a combination of volatile dynamic RAM 84 and non-volatile RAM (NVRAM) 86.

In accordance with digital broadcasts wherein digitized channels are multiplexed as data packets onto a six megahertz analog channel, the set-top box 28 also includes at least three packet identification (PID) filters 88 - 90 to extract the appropriate encoded data packets for a user-selected digital channel. Based on the user-selected display, audio and other requirements, the microprocessor 74 writes an identification

value to each of the PID filters 88 - 90, whereby the filters 88 - 90 pass only those packets corresponding to that value. As shown in FIG. 3, one of the PID filters, filter 88, provides the filtered packets to an audio decoder 92 which decodes the digital audio data (encoded according to the AC3 format), while another PID filter 90 provides filtered packets (MPEG2 encoded) to the video decoder 52.

As can be readily appreciated, in addition to line-level audio and video outputs, the resulting video signal may be output from the set-top box 28 with separate luminance and chrominance signals (SVHS format). As is typical, the set-top box 28 may also contain a modulator (not shown) for combining the audio and video signals onto a modulated carrier channel such as channel 3 or 4, for compatibility with television sets not having separate audio and video inputs.

A third PID filter 89 is provided to extract in-band and out-of-band data directed to the operation of the set-top box 28. A packet processor 94 handles those packets. The set-top box is also equipped with an on-screen display frame buffer (OSD) 96 capable of superimposing alphanumeric characters, other symbols and bitmap graphics over a displayed image. To accomplish this superimposition, an overlay 98 is provided to appropriately combine the video outputs of the video decoder 52 and the OSD 96.

The cable box 28 functions when the user provides an appropriate and valid command to the cable box 28. For example, in response to a digital channel selection command, the microprocessor tunes the in-band tuner 70 to an appropriate analog channel based on the digital channel selected by the subscriber. If a digital channel was selected, a table or the like stored in the memory 82 determines the analog channel that carries the digital channel's packets, along with the packet identification numbers corresponding to that channel, for writing into the PID filters 88 and 90. Once the PIDs have been written, the audio and video decoders 52 and 92 will receive the appropriate packets and decode and output appropriate signals. As described below with reference to the present invention, some of the packets will include page images associated with the information service.

The subscriber also will be provided with an input device, such as the hand-held remote control 76 best shown in FIG. 4. The preferred input device 76 includes four directional (up, down, left and right cursor) buttons, $100_1 - 100_4$ respectively, and a "SELECT" button 102. The remote control 76 may include a dedicated button, chosen as the "A" button 104 of FIG. 4, which may be used to enter the information service in one alternative scenario described below. The preferred remote control input device 76 will also provide the normal complement of TV-related buttons including a numeric keypad 106, volume adjustment,

channel adjustment, mute and so on. Other buttons such as those for control of a videocassette recorder also may be provided. The remote control is preferably wireless, e.g., an infrared or RF-based remote control, but of course
5 alternatively may be wired. Moreover, alternate input devices need not be remote, but may for example, be provided as a keypad (not shown) on a set-top box.

B. THE BROWSER

10 In accordance with one aspect of the invention, the user utilizes the set-top box 28 to enter and interact with the Information Service. To this end, the browser 62 has been downloaded into the memory 82 of the set-top box 28, along with APIs 66 for interfacing the browser 62 to the operating system
15 64 of the set-top box 28. The operation of the browser 62 is generally described herein with reference to the flow diagram of FIGS. 5A - 5B.

In one scenario, when the subscriber, via the remote control 76, tunes to a specified (and otherwise unused for
20 programming) channel reserved for the Information Service, the browser 62 provides the subscriber with a page image having page elements displayed thereon including links to other information. The page images are obtained from the external data source 48, ordinarily the Internet, and are Hypertext
25 Markup Language (HTML) pages provided by a third party that

have been converted to an intermediate format as described below. For example, television stations, advertisers, pollsters and the like may obtain rights to have one or more page images transmitted on the cable medium 24 for potential viewing by the consumer end-user.

As shown by steps 500 - 502 of FIG. 5A, the initial page image is preferably a default (home) page that is displayed when this particular Information Service channel is selected. Another page based on information known to the system, such as a page corresponding to the previous channel being viewed by the user, may be displayed when the user enters this channel. Although not necessary to the invention, it is feasible that more than one such channel may be provided for entering the information service, with a potentially different initial page for each channel.

By way of example, the image 108 of FIG. 6, including a number of links 110₁ - 110₅, may be the default page displayed when channel 99 is selected. For visibility purposes, the cable box 28 utilizes the on-screen display (OSD) 96 to draw focus (e.g., denoted in FIG. 6 by the visible ring, i.e., box 112 or the like) on one of the links when the page 108 is displayed. Other elements which can be focused are shown in FIG. 6 as being surrounded by dashed boxes (not ordinarily visible to an actual user). As shown by step 504, the browser 62 then waits for a command from the user. One such command is

entered as the user presses one of the directional cursor buttons 100₁ - 100₄ on the remote control 76 (FIG. 4).

As detected by step 504 and 506, when the user presses a directional cursor button 100₁ - 100₄, at step 508 the browser
5 62 reads the meta-data associated with the displayed page to determine how to adjust focus, (described below), and then draws the focus at the next location at step 510. In this manner, the user tabs through the links 110₁ - 110₅, changing the focus until a desired link is focused. Then, using the
10 SELECT button 102 (FIG. 4) of the remote control 76, (as detected by steps 504 and 512 of FIG. 5A), the user commands the browser 62 to take an action associated with the focused link. Examples of some possible actions are represented in FIG. 5B, and include hyperlinking to another display page,
15 filling in a check-box, submitting a form, and so on as described in more detail below.

If the user pushes the "A" button 104 on the remote control 76, step 514 detects this command. Since the user entered the Information Service via the service's specific
20 channel, step 516 returns the user to step 502 which displays the default page of the Information Service. In other words, pressing the "A" button in this scenario returns the user to the home page of the service. The user exits the service in this scenario by entering another channel, as detected by step
25 518.

In another scenario, the user is watching programming on a specific channel that participates in the Information Service.

If the user pushes the "A" button 104 on the remote control 76

(FIG. 4) at any time while viewing such a participating

5 channel, as detected by step 500, an initial page image (the

"top-level" page) corresponding to that channel is displayed

(step 520), along with links to other pages. For example,

(assuming station participation), a user viewing ESPN will be

shown an ESPN top-level page when the "A" button 104 is

10 pressed. As before, if the top-level page provides links, the

user can select from among those links and jump to other pages

from that top-level page, but in this scenario those links

ordinarily connect to only a small number of pages that are

recognized as being "tied" to the original video channel. The

15 user can exit the service by changing to another channel (step

518), or by again pushing the "A" button 104 (step 514). Note

that in this scenario, step 516 does not display the home page

when the "A" button is detected, but instead branches to step

522 where the set-top box is returned to the previous channel

20 and the service is exited.

Moreover, if the service was entered via the "A" button

104 (FIG. 4), the act of changing the channel resets and exits

the Information Service. For example, if a page image page

corresponding to a participating channel is being displayed,

25 and the user changes to another channel but then returns to the

original channel, the video program of the original channel will be displayed, not the page corresponding thereto.

Note that if another command is entered, (e.g., a PLAY command corresponding to a video recorder), the command can be
5 handled by the browser 62 as desired. For example, the command can be treated like a channel selection (exiting the service) or just ignored. Steps 524 - 526 are shown to generally represent receipt of such a command.

In any event, if the user selects a page in the service
10 and does not immediately select a link, it is possible for the page image to be updated at a frequency equal to the maximum initial latency of the carousel 50. At present, a nominal maximum latency for an image to cycle back for display is about eight seconds, but this is variable depending on the amount of
15 carousel bandwidth dedicated to a given page. More particularly, a frequently accessed page may be placed in the carousel 50 more than once at spaced-apart locations to reduce the latency for that page by increasing its frequency therein. For example, the service home page may be placed in the
20 carousel 50 four times, providing a maximum latency of approximately two seconds for that page.

To facilitate the user interaction, once the service has been entered and a page is displayed, (step 502 or step 520), using the OSD 96, the browser 62 in the digital set-top box 28
25 draws focus on the first page element listed in a

FocusDescriptor list in the meta-data (described below) associated with that page. The geometry (shape) of the indicator (i.e., the focus ring) drawn by the OSD 96 is also determined by information in the FocusDescriptor list. It is
5 also feasible to specify the color, shading and the like of the focus ring in the meta-data.

As described above, the user may change the focus via the direction buttons 100₁ - 100₄ on the remote control 76, whereby the focus is re-drawn on the appropriate element (step 510).

10 More particularly, the order of changing focus in response to a directional button, i.e., the focus chain, is specified by the focus descriptors that are carried in the page meta-data. The focus descriptors explicitly specify where focus should be next drawn when the user depresses the up, down, left or right
15 buttons 100₁ - 100₄ on the remote control device 76. For remote controls lacking direction keys, a single button can be used to tab through the links, in which event the order in which the focus descriptors occur in the focus descriptor list determines the focus chain.

20 In either arrangement, while focus is rendered on a particular element, the user may select that element by pressing the SELECT button 102 on the remote control 76 (step 512), or an equivalent button (e.g., ENTER button) available on other devices. Regardless of how selected, when the element is
25 selected, the browser 62 takes an appropriate action. The

following table summarizes the actions taken by the browser for various types of page elements.

Element	Tag	Drawing Required	Browser action
Text Anchor	<A HREF= <i>url</i> > <i>anchor text</i> 	Focus	On selection jump to page indicated by URL.
Image Anchor	<A HREF= <i>url</i> > <IMG SRC= <i>url</i> > 	Focus	On selection jump to page indicated by URL.
Client Image Map	<AREA SHAPE= <i>shape</i> COORD= <i>coord</i> HREF= <i>url</i> >	Focus	On selection jump to page indicated by URL.
Automatic Hyperlink	<META HTTP-EQUIV=REFRESH CONTENT="delay; URL= <i>url</i> ">	None	Jump to page indicated by URL automatically after delay (in seconds).
Guide Hyperlink	<A HREF= <i>url</i> > GUIDE 	Focus	On selection pass the URL string to the GUIDE.
One Line Text	<INPUT TYPE=TEXT>	Focus "0"-"9"	Echo numerals when they are entered on the keypad. No action on selection.
Password	<INPUT TYPE=PASSWORD>	Focus "*"	Echo "*" when numerals are entered on the keypad. No action on selection.
Radio Buttons	<INPUT TYPE=RADIO>	Focus Check	On selection mark the button as checked and clear other buttons that are part of the button group.
Check-Box	<INPUT TYPE=CHECKBOX>	Focus Check	On selection mark the checkbox as checked.
Submit	<INPUT TYPE=SUBMIT>	Focus Border	On selection post the form query string for upload. Jump to the URL specified by the DESTINATION attribute in the <FORM> tag.
Reset	<INPUT TYPE=RESET>	Focus Border	On selection reset the form elements.
Image	<INPUT TYPE=IMAGE>	Focus	On selection Post the form query string for upload. Jump to the URL specified by the DESTINATION attribute in the <FORM> tag.
Hidden	<INPUT TYPE=HIDDEN>	None	Not selectable

To select and display a carousel page, the browser 62 generally follows the steps set forth in the flow diagram of FIG. 7. First, as represented by step 700, the browser determines a page to display, i.e., a default page or a linked
5 page. At step 702, the browser 62 references meta-data associated with that page to determine the page group to which that page belongs, and the digital channel corresponding thereto. As described in more detail below, a one-to-one mapping exists between a page group and a digital channel, and
10 nine-to-one mapping exists between carousel pages and digital channels.

Cable boxes typically provide APIs 66 to control the tuner and selection of program elements in the MPEG2 stream. The browser 62 uses such an API (in the APIs 66) to specify the
15 digital channel corresponding to the appropriate page group on the carousel 50, whereby the microprocessor 74 in the set-top box 28 tunes the in-band tuner 70 to the appropriate carrier (step 704) and selects the program (Service) corresponding to the desired page group (step 706). Note that the mapping
20 between digital channels and carousel page programs is fixed. Next, at step 708, the browser 62 selects the program element (service component) containing the carousel page for display, and uses an API (or the like) to select the Video Program Element for display (step 710). As a result of this step, the

PID is written to the PID filter 90 and the page image is decoded and displayed by the hardware.

At step 712, the Browser 62 selects the program element that carries the meta-data for the page group. Cable boxes may provide an API for this function, this time to acquire an identifier for the page meta-data. At step 714, the browser 62 reads the page meta-data, which, as described in more detail below, includes a record for each element on the page. Each element record includes information such as the geometry of focus for that element and other information specific to that element. For anchor elements, (described below), the record includes the digital channel and program element for the page to which the link refers. Note that the carousel 50 contents are completely described by the carousel meta-data, which is carried in-band. No out-of-band or backchannel data transmission is required to navigate between pages in the carousel 50.

After the meta-data has been read (step 714) by the browser 62, at step 716, the browser 62 draws focus on the default link as specified by the page meta-data. At this time, the page is ready for user-interaction. For example, as described above, the browser 62 draws focus on other links as they are tabbed to by the user, according to the focus chain specified in the page meta-data.

The browser 62 supports a subset of HTML anchors. The processing of each type of anchor is described below. The following table gives a brief summary of anchors supported by the Information Service.

Element	Tag	Support	Attribute Support	Limits	Drawing Required	Notes
Text Anchor	<A HREF= <i>url</i> > <i>anchor text</i> 	Yes			Focus	Specifies text hyperlink. HREF indicates destination.
Image Anchor	<A HREF= <i>url</i> > <IMG SRC= <i>url</i> > 	Yes			Focus	Specifies image hyperlink. HREF indicates destination.
Client Image Map	<IMG SRC= <i>url</i> USEMAP= <i>map</i> > <MAP NAME= <i>map</i> > <AREA SHAPE= <i>shape</i> COORD= <i>coord</i> HREF= <i>url</i> > </MAP>	Yes			Focus	Specifies client-side imagemap. HREF indicates destination.
Server Image Map	<A HREF= <i>CGIurl</i> > <IMG SRC= <i>url</i> ISMAP> 	No				Use client-side image map.
Automatic Hyperlink	<META HTTP-EQUIV=REFRESH CONTENT=" <i>delay</i> ; URL= <i>url</i> "> SLIDESHOW=YES	Yes				Hyperlink specified by URL is automatically taken after delay (in seconds).

5

The focus geometry for anchors and areas in imagemaps are specified in the page meta-data. The browser 62 uses this information to draw focus on hyperlinks and to select other pages for display when hyperlinks are selected. The page meta-
 10 data also specify the focus chain. At present, the browser 62 handles text anchors, image anchors, and areas within imagemaps identically. Thus, when the user moves focus to a hyperlink,

the browser 62 simply draws focus, using the OSD 96, on some region of the screen as indicated by geometry information in the page meta-data. When the user selects the link, the browser 62 changes the display to the destination page as indicated by the link data in the former page's meta-data.

At present, it is not possible to specify explicitly that an anchor within a page should receive initial focus. Instead, the first anchor or imagemap in the HTML source will be the element that receives initial focus when a page is first displayed. Within an imagemap the order of the <AREA> tags will determine the order of focus within that imagemap. The order of the tag within the HTML source will determine where the imagemap anchors will occur in the focus chain. Note that it is possible to edit the focus chain for a page at page conversion time, (described below), in order to achieve results that cannot be generated simply in an HTML source.

Automatic hyperlinks are allowed, in which after the page is displayed and the delay (specified in meta-data) has elapsed, the browser 62 displays the page to which the hyperlink refers. As before, the page meta-data of the former page includes information that the browser 62 uses to select the destination page for display. Nothing is rendered in response to an automatic hyperlink.

A server-side slideshow may also be indicated, in which a series of still images is sequentially displayed on the same

page. Unlike a client-side autolink to another page, (which can produce a similarly-appearing client-side slideshow using multiple pages), the page change for a server-side slideshow takes place at the server side. Via the slideshow tag, the server 46 inserts a new page image in place of the old with each new cycle of the carousel 50. On the client side, the displayed slideshow page autolinks to itself to reacquire page meta-data. The slideshow feature enables the injection of a series of still images with appropriate meta-data, while only using a single page of the carousel 50. Moreover, the server 46 may obtain the series of images in advance, eliminating real-time downloading thereof. By way of example, a real estate entity may use this feature to present a series of images of new homes with accompanying meta-data, but only use one page of those available in the carousel 50. Note that a slideshow can present an image for any multiple of the carousel revolution time, e.g., eight seconds, by replicating images in a series as desired.

Moreover, this feature can be used in conjunction with client-side autolinks (using more than one page) to produce other update intervals. Indeed, by rebuilding the carousel, animation may be accomplished. To this end, a plurality of still images with slight changes from image to image will appear as animated movement. If a single-page slideshow, the animation may appear somewhat slow depending on the latency

(e.g., a movement every eight seconds). However, with autolinks to multiple pages, the animation may be sped up. Note that MPEG2 is arranged to transmit change information between frames, and thus not much bandwidth is required to accomplish animation. Other image enhancements such as brightening a focus ring, adding images together and so on may be performed by rebuilding the carousel, taking advantage of MPEG2 features wherever possible.

In keeping with the invention, the browser 62 supports a subset of HTML forms with a few extensions. The processing of each of the form elements is described below. The following table gives a brief summary of forms supported by the Information Service. Only those attributes listed are supported at this time.

Element	Tag	Support	Attribute Support	Limits	Drawing Required	Notes
Action	<FORM ACTION= <i>url</i> >	Yes	ACTION METHOD ENCTYPE DESTINATION= <i>url</i>			Form submission is standard syntax but is not sent via HTTP until the STB is polled.
One Line Text	<INPUT TYPE=TEXT>	Yes	NAME SIZE ALIGN DISABLED	Numeric Only MAXLENGTH == SIZE	Focus "0"- "9"	Intended for credit card number and quantity entry only. No editing of field. User must use Reset to clear field.
Multiple Line Text	<TEXTAREA>	No				
Password	<INPUT TYPE=PASSWORD>	Yes	NAME SIZE ALIGN	Numeric Only MAXLENGTH == SIZE	Focus "*"	Intended for PIN entry only. No editing of field. User must use Reset to clear field. Characters are not echoed.
Drop Menus	<SELECT>	No				Use radio buttons
Text Menus	<SELECT MULTIPLE>	No				Use radio buttons
Graphic Menus	<SELECT MULTIPLE SRC= <i>url</i> >	No				Use radio buttons
Radio Buttons	<INPUT TYPE=RADIO>	Yes	NAME VALUE CHECKED ALIGN		Focus Check	
Check-Box	<INPUT TYPE=CHECKBOX>	Yes	NAME VALUE CHECKED ALIGN		Focus Check	
Range	<INPUT TYPE=RANGE>	No				Use type=TEXT
Submit	<INPUT TYPE=SUBMIT>	Yes	NAME VALUE ALIGN		Focus Border	
Reset	<INPUT TYPE=RESET>	Yes	NAME ALIGN		Focus Border	Allows simple edit control for text entry. User can only reset all fields.
Image	<INPUT TYPE=IMAGE>	Yes	NAME SRC ALIGN		Focus	
Hidden	<INPUT TYPE=HIDDEN>	Yes	NAME VALUE AUTOSUBMIT		None	Information Service specific VALUES will return textual user information (Name, Address, Phone)
Button	<INPUT TYPE=BUTTON>	No				Use type=SUBMIT
Scribble	<INPUT TYPE=SCRIBBLE>	No				

Using forms, a page can have simple data entry links, including check boxes, radio buttons, and numeric entry (text boxes). By way of example, FIG. 8 shows an exemplary page 116

including text boxes 118₁ - 118₄, radio buttons 120₁ - 120₄, and a check box 122. In addition, the page 116 includes a button 124 for submitting an order, a "RESET" button 126 for clearing entries, and a hyperlink element 128. In FIG. 7, focus is shown (by the solid rectangular ring) as being on the "PURCHASE NOW" submit button 124, while elements which can be focused are shown surrounded by dashed boxes (not ordinarily visible to an actual user).

One such form is a guide form, which is processed in real time by the programming guide to take an appropriate action upon user submission thereof. As described below, depending on the current time, the programming guide allows a user to link to a currently available program, add the program to a timer for timed viewing thereof, and/or prompt the user to purchase a pay-per-view event.

Another type of form is for purchasing merchandise or the like. To perform a purchase with this type of "store-and-forward" form, the user tabs through the various elements to select and enter appropriate information. The entered attributes (e.g. color, size, style, quantity, payment method and so on) are temporarily stored in the memory 82. Once the appropriate data is entered in this manner, the user selects the "PURCHASE NOW" link 124, which stores the selected information as data 130 (FIG. 3) (preferably in the non-volatile memory 86) in the set-top box 28. At a later time,

the purchase information will be collected from the set-top box 28 with a polling procedure, whereby each box in the cable system 20 is directed in turn to call a polling server 132 via its modem 134 (FIG. 3), typically late at night.

5 More particularly, in a preferred embodiment of the present invention, there is no real-time interaction with a web server. As a consequence, form submission must be emulated. The meta-data for a page image includes all the necessary information required to generate a standard URL query string.

10 When a form is submitted, data including the ACTION URL, the query string, and METHOD are stored as data 130 (preferably in NVRAM 86) in the set-top-box 28 as an ASCII string. These data are formatted exactly like a standard URL query string. The METHOD, GET or POST is appended to the form query string. In

15 other words, a form element named METHOD is appended to every form query string automatically. For instance, "&METHOD=GET". An upload forms server 132 of the Information Service removes this sub-string when the form data are processed.

When the set-top-box 28 is polled via its modem 134 for

20 the return data (typically once per day), the form data for all such forms which have been submitted are returned to the upload forms server 132 of the Information Service. The server 132 processes the form data and generates the appropriate HTTP GET or POST requests to the specified ACTION URL. Of course, user

25 information, including name, billing and mailing addresses, and

credit card type and number, will need to be collected from each user before a purchase can be made. This information can either be held remotely by the polling server 132, or stored within the set-top box 28 to be sent with each purchase. If
5 this information is not available or valid, then the "PURCHASE NOW" button will link to an "error" page in the carousel, which will direct the user to call the service provider.

No immediate confirmation of the purchase will be available. The CGI scripts for Information Service forms
10 cannot return HTML documents to subscriber-users since the contents of the carousel are broadcast and not unicast. However, the CGI forms script can send Email to the user in response to a forms query. To this end, the Email address of a particular set-top-box can be returned with the form data by
15 using the Magic Element Name _EMAIL in a HIDDEN form elements (described below). Thus, an e-mail confirmation notice may be sent to the user, as described below with reference to the e-mail scenario.

The focus geometry for form elements is specified in the
20 page meta-data, described below. As before, the browser 62 uses this information to draw focus on the form elements. At present, it is not possible to specify that a particular form element has the default focus for that form. Instead, the first form element in the HTML source will be the first element
25 that receives focus when the user tabs to the form. It is also

not presently possible to specify that a particular form element has the default focus for the page in which that element is contained. If, however, the form is the first element in the HTML source, then the first element in that form
5 will receive the initial focus.

Note that for high-quality imaging, (relative to the low quality provided by the OSD 96), the face of a submit button (such as the "PURCHASE NOW" link 124) is rendered at page conversion time as part of the compressed page image. The
10 button borders, however, are rendered at display time using the OSD 96 of the set-top-box 28. The page meta-data includes information that the browser 62 uses to draw button focus as well as drawing button borders.

As a result, when the user selects a submit button, the
15 browser 62 directs the OSD 96 to draw the button borders such that the button appears to be depressed and released. As generally shown in FIGS. 5A - 5B, when the user selects a submit button (step 512, FIG. 5A and step 530, FIG. 5B), the browser 62 then queues the appropriate form query string (step
20 532) for upload as described above, (or for processing by the program guide as described below). If a DESTINATION attribute is specified on the containing form, (as detected by step 534), then following the submit command the browser 62 will jump to the page corresponding to that destination (step 536).

Similarly, a reset button face (e.g., "RESET" button 126) is rendered at page conversion time as part of the compressed page image. The button borders are likewise rendered at display time using the OSD 96 of the set-top-box 28 so that the button appears to be depressed and released. The page meta-data includes information that the browser 62 uses to draw button focus as well as drawing button borders. When the user selects the reset button (step 538), the browser 62 appropriately draws the button borders and restores the form elements to their default state (step 540).

Any page that contains a text entry box or password box (described below) contains a reset button so that the user can clear errors. At present, the text entry and password boxes allow entry but do not support any other type of editing.

Any submit element, e.g., a "SUBMIT" button or a submit image element, is also rendered at page conversion time as part of the compressed page image. The page meta-data includes information that the Browser 62 uses to draw focus on the image. When the user selects the Submit Image, the Browser 62 queues the appropriate form query string for upload or processing by the guide. If a DESTINATION attribute is specified on the containing form then the Browser 62 will jump to that page.

Check boxes are also rendered at page conversion time as part of the compressed page image. Since a check mark may or

may not appear based on the user entry, the check mark is rendered at display time using the OSD 96 of the set-top-box 28. The page meta-data includes information that the browser 62 uses to draw box focus as well as drawing the check marks on the box. When the user selects a check box (step 542), the browser 62 inverts the state of the box (step 544) in the memory 82 and correspondingly changes the display by either drawing or erasing a checkmark (shown as an "X" in box 122 of FIG. 8) on the selected checkbox. When the form is submitted, the boxes that are checked result in name/value pairs in the form query string.

Similarly, radio buttons are rendered at page conversion time as part of the compressed page image. The user-movable check (shown as a darkened circle in box 120₂ of FIG. 8), however, is rendered at display time using the OSD 96 of the set-top-box 28. The page meta-data includes information that the browser 62 uses to draw button focus as well as drawing check marks on the button. When the user selects a radio button (step 546), the browser 62 sets the state of that button to selected while de-selecting others with the same name. At step 548, the browser 62 also causes the OSD to draw a suitable checkmark on the button, and erase the checkmarks on any other buttons with the same name. When the form is submitted, the button that is checked results in a name/value pair in the form query string.

At present, a Text Entry Box only supports entry and echo of the numerals "0" through "9," and only a single font and pitch are supported. A Text Entry Box is rendered at page conversion time as part of the compressed page image. Echoed
5 text is rendered at display time using the OSD 96 of the set-top-box 28. The page meta-data includes information that the browser 62 uses to draw focus as well as information for drawing the characters.

When a text box is selected at step 512 (FIG. 5A) and 550
10 (FIG. 5B), the browser 62 draws focus on the text box. If the user depresses a number key on the keypad then at step 552 that number is displayed in the leftmost position of the text box and advances the text entry position to the next character position. No cursor is presently displayed to indicate the
15 text entry position, and the next character is simply the rightmost unoccupied character position in the text box. When the user depresses another number key on the keypad, that number is displayed in the new character position and the text entry position is advanced. When the form is submitted a
20 name/value pair is appended to the form query string.

Certain rules for text boxes presently apply. If the user attempts to enter more than characters then allowed in the SIZE field of the meta-data (described below), those characters are ignored. Moreover, for now a text box does not support any
25 type of editing, and thus in order to clear errors, the user

uses a reset button on the form. No default values (using the VALUE attribute) may be specified for text boxes. The Password Box is identical in function to the text box except that the characters are not echoed. Instead, an asterisk ("*") or the
5 like is displayed at step 552 for every character that is entered.

The browser 62 also supports the DISABLED attribute, (seldom supported by legal HTML), which, when used in conjunction with the magic name "_TOTAL" can be used to
10 generate a read-only text box which displays the total cost of a purchase transaction. For instance the tag <INPUT TYPE=TEXT NAME=_TOTAL SIZE=5> will generate a text box 5 characters in size in which the following result is displayed :

_TOTAL = _QUANTITY * _PRICE + _SANDH, where _QUANTITY is
15 presumably to be entered by the user in a text box (e.g., the text box 118₄) and _PRICE and _SANDH are specified using hidden text. Such a read only text box 136 is shown in FIG. 8.

Hidden text results only in page meta-data. Nothing is rendered either at page conversion time or at display time.

20 When a form is submitted Hidden Text results in a name/value pair being appended to the form query string.

Certain state information stored within the set-top-box may be returned as part of the form query string by using "magic element names" for the NAME of the hidden text. In such
25 an event, no VALUE need be specified.

The Information Service of the present invention adds two attributes to the standard HTML syntax. More particularly, a first way in which the Information Service extends the standard HTML hidden text syntax is by adding the attribute AUTOSUBMIT
5 to the tag <INPUT TYPE=HIDDEN>. When the user leaves a page with a form containing a hidden text element with the AUTOSUBMIT attribute, the form query string is queued for upload just as if the user had selected a submit button.

Second, the attribute DESTINATION has been added to the
10 tag <FORM>. This tag causes the Browser 62 to jump to the specified page when the user submits the form. This allows the author to specify an HTML page that simulates the result of the HTTP GET on normal form submission (e.g., through CGI). This tag is unique to the Information Service system.

15 For any page, it is possible to include a link that tunes the set-top box 28 to a video channel rather than a link to another page. To this end, the Information Service facilitates interaction with a programming guide (e.g., PreVue). The exact behavior of the link depends on the type of video program that
20 is selected. If the link selects a channel with no time (of day) associated therewith, or selects a channel with a time that indicates a currently available program, the set-top box immediately tunes to the selected channel. If the associated time is in the future, the user is presented with a programming
25 guide pop-up window and prompted to add the program to a timer.

for timed viewing thereof. If the program is a pay-per-view event, the user is prompted to buy the event, and, if purchased, the browser 62 either tunes to the channel or adds the program to the timer.

5 To accomplish such actions, the Information Service provides access to functions in the programming guide through the use of forms. A form that accesses the guide does so by specifying an ACTION URL that is processed by the guide, that is, the guide looks like a web-server running a CGI script.

10 One such guide is accessed using the URL
"http://www.prevue.com/cgi/guide".

 At page conversion time, this URL is recognized, and meta-data for the page indicate that the form query string should be submitted to the guide for processing. At page
15 display time, when the form is submitted, the browser 62 submits the form query string to the guide rather than queue it for upload. To reduce meta-data size and simplify argument processing, the query string is preferably collapsed into a compact binary representation thereof at page conversion time.
20 This syntax allows page image authors to access guide emulation (e.g., provided by PreVue) at author time. The following table sets forth the queries that are supported by the guide:

Function	Query Syntax	Description
TUNE	Function=TUNE &SourceID=program_name &Time=now	Switch to a television program
REMIND	Function=TUNE &SourceID=program_name &Time=some future time	Set a reminder for a television program
RECORD	Function=REC &SourceID=program_name &Time=some future time	Set a reminder for a television program
EMAIL HELO	Function=HELO	Opens EMAIL session
EMAIL QUIT	Function=QUIT	Closes EMAIL session
EMAIL DATE	Function=DATE &UpperLeft=xlocation+ylocation &LowerRight=xlocation+ylocation	Display current message RFC822 "Date" text at the specified screen location.
EMAIL FROM	Function=FROM &UpperLeft=xlocation+ylocation &LowerRight=xlocation+ylocation	Display current message RFC822 "From" text at the specified screen location.
EMAIL SUBJ	Function=SUBJ &UpperLeft=xlocation+ylocation &LowerRight=xlocation+ylocation	Display current message RFC822 "Subject" text at the specified screen location.
EMAIL BODY	Function=BODY &UpperLeft=xlocation+ylocation &LowerRight=xlocation+ylocation	Display current message RFC822 message body text at the specified screen location.
EMAIL ACKS	Function=ACKS	Save the current message and increment the current message indicator.
EMAIL ACKD	Function=ACKD	Delete the current message and increment the current message indicator.
EMAIL ACKB	Function=ACKB	Save the current message and decrement the current message indicator.

IV. PAGE IMAGES

As described above, the carousel of page images and meta-
5 data are carried as a single MPEG2 Transport Stream, and each
page image is a single MPEG2 video sequence consisting of a

single I-Frame image of the rendered HTML page. As generally represented in the program map tables 138₁ - 138_n of FIG. 9, each page image is carried as a single program element (i.e., Service Component) of a program (i.e., Service), and, (as
5 limited by the DCT1000 set-top box), each program (Service) ordinarily consists of ten program elements. As further seen in the program map tables 138₁ - 138_n of FIG. 9, nine of the program elements (i.e., a page group) contain page images, and the other program element contains the meta-data for the nine
10 page images that make up the program. The meta-data are carried as the first program element within a program.

As also represented in FIG. 9, each group of nine image pages in the carousel 50, which correspond to a distinct program, is mapped to a single digital channel. Thus, (as
15 described above with reference to FIG. 7), in order to display a particular page, the browser 62 tunes to the appropriate digital channel and selects the appropriate program element (Service Component) for display. The browser 62 also selects the first (meta-data) program element so that it can render
20 focus and execute links as directed by the user. The transport stream includes the appropriate PSI data to allow the page images to be selected and displayed.

According to digital transmission conventions, the program map table 138₁ - 138_n (i.e., Service Definition Table)
25 maintained for each program contains 10 entries, and, including

the PID which carries the program map table, thus uses 11 PIDs. A program association table 139 (Service Association Table) associates programs with program map PIDs and thus contains as many entries as the number of carousel pages divided by nine.

- 5 The maximum number of page images that may be carried by a single carousel 50 is limited to 6700 pages. Note that if PCRs must be supplied to ensure that the set-top-box NTSC sub-carrier does not drift, then a single valid PCR stream will be multiplexed with the carousel data. The program map table for
10 all programs references this PID as the PCR_PID.

Pages are delivered to the server in a two-stage process. First, a content provider transfers information (from an external source such as the Internet 48) to the Information Service server 46, the information including provider
15 identification, a root URL of the content, and the date and time the content is to become valid. Any acceptable protocol for this transmission is feasible, including Hypertext Transfer Protocol (HTTP) or a private message protocol on top of TCP/IP.

Second, using HTTP, the Information Service server gathers
20 the content at the specified URL and stores it for processing into the carousel 50. The timing of this transfer may vary depending on several factors, including available storage at the server, number of pending transfers, date and time the content is to become valid and default actions specified by the
25 cable operator. In any event, the content is transferred

before the start time. For real-time updates (e.g. sports, scores or stock information), the same process is followed, but with an immediate start time. The system is designed to allow for low latency for both the information transferring and content gathering stages.

As generally represented in the block diagram of FIG. 10, a conversion process 142 converts the page 140 into an intermediate page format 144, where it is passed to a carousel builder 146. One purpose of the intermediate page format is to reduce the amount of processing that needs to be performed by the processor 74 at the cable end. For example, rather than have the cable end processor dynamically calculate from an HTML page layout where to jump in response to a cursor key, the jump is pre-decided and stored in the intermediate page format.

The IPF file includes an image tag, a program information tag and a meta-data tag as described below. Note that the values correspond with fields within the meta-data as described herein.

Image tag

<META NAME=PARAKEET_IMAGE CONTENT="*Url*">

where *Url* represents the URL of the MPEG video file, (e.g., www.content.com/Page1.M2V).

Program information tag

<META NAME=PARAKEET_PROGRAM_INFO CONTENT="

PROGRAM=*Program* ELEMENT=*Element* PACKAGE=*Package*

">

where PROGRAM=**Program** specifies the program_number or SourceID of the page. This is only relevant for quick pages, i.e., a page that is mapped as a channel, (for example, channel 100 might be the weather page). ELEMENT=**Element** specifies the program_element or ServiceComponentID of the page (only relevant for quick pages), and PACKAGE=**Package** specifies the package number for premium or tiered services.

Meta-data tag

```

10 <META NAME=PARAKEET_METADATA CONTENT="
    _PAGE_META_DATA TYPE=Type AUDIO=Url DELAY=Time
15 _ELEMENT_DESCRIPTOR TYPE=Type
    _LINK_DESCRIPTOR Url
    _FOCUS_DESCRIPTOR SHAPE=Shape COUNT=CoordCount UP=UE DOWN=DE
    RIGHT=RE LEFT=LE COORDS=X,Y,X,Y,...
    _FORM_DESCRIPTOR NAME=Name VALUE=Value COORDS=X1,Y1,X2,Y2
20 _FORM_DESCRIPTOR FUNCTION=Function TIME=Time COORDS=X1,Y1,X2,Y2
    ">

```

The PAGE_META_DATA contains the per-page meta-data, wherein TYPE=**Type** indicates the type of the page (e.g. Hold, Reload, Autolink, and so on), AUDIO=**Url** identifies the URL of the background audio file (e.g., www.sounds.parakeet.com/classical.ac3), and DELAY=**Time** specifies the delay in seconds for Autolink pages. For each element on the page one or more of the following tags will be found, and will be grouped together such that the tags for a particular element occur together, (_ELEMENT_DESCRIPTOR,

_LINK_DESCRIPTOR, _FOCUS_DESCRIPTOR, _FORM_DESCRIPTOR). Note that there are two formats for the _FORM_DESCRIPTOR. The following describes the information in the tag:

5 TYPE=**Type** - the element type (e.g. LINK, FORM, INPUT_SUBMIT, and so on),

Url - for elements that link the URL of the destination page (e.g. www.contentprovider.com/pageN.ipf),

10

SHAPE=**Shape** - shape of the focus, (e.g., CIRCLE, RECT, POLYGON),

COUNT=**CoordCount** - the number of coordinates for focus,

UP=**UE** - the element to receive focus on up-button press,

DOWN=**DE** - the element to receive focus on down-button press,

15 RIGHT=**RE** - the element to receive focus on right-button press,

LEFT=**LE** - the element to receive focus on left-button press,

COORDS=**X,Y,X,Y,...** - the Coordinates for focus,

NAME=**Name** - the NAME attribute of form element

20 VALUE=**Value** - the VALUE attribute of form element

COORDS=**X1,Y1,X2,Y2** - the coordinates of form element (e.g., the button corners),

FUNCTION=**Function** - the GUIDFORM function (e.g. TUNE),

TIME=**Time** - the effective time for TUNE or REC function, and

COORDS=X1,Y1,X2,Y2 - the coordinates for text field on GUIDEFORMs.

The following shows an example of an IPF file for a simple page

5 only containing links:

```

10 <META NAME=PARAKEET_ORIGINAL_HTML_CONTENT="
    <!--META HTTP-EQUIV="Refresh" CONTENT = "5; URL = page17.htm"--
    >
    <HTML><BODY SCROLL=NO BGCOLOR=BLACK leftmargin=0 topmargin=0>
    <IMG SRC=Weather1.jpg BORDER=0 USEMAP="#coords">
    <MAP NAME="coords">
    <AREA SHAPE=RECT COORDS="427,36,583,68" HREF="page17.htm">
    <AREA SHAPE=RECT COORDS="502,385,584,445" HREF="page0.htm">
15 <AREA SHAPE=RECT COORDS="425,108,585,142" HREF="page5.htm">
    <AREA SHAPE=default HREF="page0.htm">
    </MAP>
    </BODY></HTML>
    ">
20 <META NAME=PARAKEET_IMAGE_CONTENT="Page1.M2V">

    <META NAME=PARAKEET_PROGRAM_INFO_CONTENT="PROGRAM=16129
    ELEMENT=0 PACKAGE=0">
25 <META NAME=PARAKEET_METADATA_CONTENT="

    _PAGE_META_DATA TYPE=HOLD AUDIO=NONE DELAY=0

30 _ELEMENT_DESCRIPTOR TYPE=LINK
    _LINK_DESCRIPTOR page17.ipf
    _FOCUS_DESCRIPTOR SHAPE=RECT COUNT=2 UP=2 DOWN=1 RIGHT=1 LEFT=2
    COORDS=237,36,323,68

35 _ELEMENT_DESCRIPTOR TYPE=LINK
    _LINK_DESCRIPTOR page0.ipf
    _FOCUS_DESCRIPTOR SHAPE=RECT COUNT=2 UP=0 DOWN=2 RIGHT=2 LEFT=0
    COORDS=279,385,323,445

40 _ELEMENT_DESCRIPTOR TYPE=LINK
    _LINK_DESCRIPTOR page5.ipf
    _FOCUS_DESCRIPTOR SHAPE=RECT COUNT=2 UP=1 DOWN=0 RIGHT=0 LEFT=1
    COORDS=236,108,324,142
    ">
45
```

To build the carousel 50, the carousel builder 146 generally follows the steps of FIG. 11, whereby at step 1100 a program element (Service Component) is allocated from the program (Service) which will carry the page and its meta-data.

5 Note that there is a one-to-one mapping between program elements and pages and a nine-to-one mapping between pages and programs. At step 1102, the page image is then wrapped with the appropriate Transport Stream systems-layer syntax using the appropriate PID from the program map table (Service Definition Table). Then, at step 1104, the page meta-data are wrapped in the appropriate private_message_stream syntax and Transport Stream syntax, using the appropriate meta-data PID from the Program Map Table.

At step 1106, the meta-data (described below) for any
15 pages that contain links to the (newly provided) page are modified to contain the program number and program element for this page. Similarly, at step 1108, the meta-data for the newly-provided page is modified to contain the program number (SourceID) and program element (Service Component) for pages
20 that are linked to by the page. The initial state of the link program number in the page meta-data is such that a Null page is indexed. The Null page resides on program number 1, and contains an image indicating that the page is not available. Lastly, as represented by step 1110, when the carousel 50 is
25 ready for transmission, the information server 46 periodically

takes each carousel image stored in the 50 and injects the image onto the transmission medium 24, a process which continues for the carousel 50 until page information therein is changed. As a result, pages are periodically available at the subscriber end as described above.

The carousel builder 146 maintains a carousel description that is modified by page update messages. Each time the carousel 50 changes, the carousel builder 146 creates a new carousel image (in server memory) from the carousel description and the pages (stored on disk). When the new carousel image is completed, it replaces the old carousel at the beginning of the next cycle. Note that in the case of pages that change each cycle, i.e., "slide show" pages, a new carousel must be built for each cycle.

V. META-DATA

In order for the user to interact with the pages, the page images have meta-data and PSI data associated therewith in the Transport Stream. In general, the carousel page meta-data contain the information necessary for the browser 62 to render focus on the links on the page corresponding thereto. The meta-data also contain information for selecting a new page image when the user selects a link, gather form input from a subset of Hypertext Markup Language (HTML) form elements and/or post form input for deferred processing.

The meta-data for a page group (of nine pages) are carried in a single program element consisting of private_stream_messages. To associate the appropriate meta-data with its corresponding page, the meta-data is fragmented into multiple private_stream_messages such that the meta-data for a particular page is carried as a unique session. Each private_stream_message is capable of containing a predetermined number of bytes of meta-data. The meta-data for a page consists of four tables, identified herein as the page element table, the link table, the focus table, and the form table. These tables are described in more detail in the following sections.

The following table provides a high-level description of the information that is carried in the meta-data for various HTML constructs:

HTML Tag	Meta-data content	Description
	Focus Specifier Page Address	Describes how to draw focus on the link and the program_number and Program Element that carry the destination page
<AREA SHAPE=shape COORDS=coords HREF=url>	Focus Specifier Page Address	Describes how to draw focus on the link in a client-side image-map and the program_number and Program Element that carry the destination page
<FORM ACTION=url DESTINATION=url>	Transaction URL Page Address	Indicates where the form result should be posted. When the form is submitted, the DESTINATION page is displayed.
<INPUT TYPE=SUBMIT>	Focus Specifier Location Specifier	Describes how to draw focus and borders on the SUBMIT button and indicates that form should be posted when the button is selected.
<INPUT TYPE=IMAGE SRC= url>	Focus Specifier	Describes how to draw focus on the image and indicates that the form should be posted when the image is selected.
<INPUT TYPE=HIDDEN AUTOSUBMIT>		Indicates that the form should be submitted automatically when the user leaves the page.
<INPUT TYPE=HIDDEN NAME=name VALUE=value>	Form Element Name Form Element Value	Indicates that the name/value pair should be submitted with the form. Nothing is displayed.
<INPUT TYPE=HIDDEN NAME=magic_name>	Form Element Name	Same as above but the value is retrieved from the local user database based on the name.
<INPUT TYPE=CHECKBOX NAME=name VALUE=value>	Focus Specifier Location Specifier Form Element Name Form Element Value	Describes how to draw focus and draw check on checkbox. Indicates name/value pair to be returned if the box is checked.
<INPUT TYPE=RADIO NAME=name VALUE=value>	Focus Specifier Location Specifier Form Element Name Form Element Value	Describes how to draw focus and draw check on radio button. Indicates name/value pair to be returned if the box is checked.
<INPUT TYPE=TEXT NAME=name VALUE=value >	Focus Specifier Text Specifier Form Element Name Form Element Value	Describes how to draw focus and draw text on the text entry element and the initial value. Only numerals are supported. No edit control, user must use RESET to clear the field.
<INPUT TYPE=PASSWORD NAME=name>	Focus Specifier Text Specifier Form Element Name	Describes how to draw focus and draw text on the password entry element. Only numerals are supported. They are echoed as "*". No edit control, user must use RESET to clear the field.
<INPUT TYPE=TEXT NAME=_TOTAL>	Location Specifier Form Element Name	No focus is rendered on this element. It is output only and numeric only. The value is the product of the magic names _QUANTITY and _PRICE added to SANDH.
<INPUT TYPE=RESET>	Focus Specifier	Describes how to draw focus on the RESET button and indicates that form elements should be reset when the button is selected.
<META HTTP-EQUIV= REFRESH CONTENT="delay; URL=url">	Page Address Delay	Causes the browser to jump to the specified URL after the specified delay automatically.

The page Meta-data contains all of the meta-data for a page, as described in the following table:

Syntax	No. of bits	Mnemonic
PAGE_META_DATA(){		
ID	16	Uimsbf
Type	8	Uimsbf
Reserved	8	Uimsbf
Delay	16	Uimsbf
Reserved	16	Uimsbf
LinkOffset	16	Uimsbf
FocusOffset	16	Uimsbf
FormOffset	16	Uimsbf
for (i=0;i<LinkOffset;i++){		
LINK_DESCRIPTOR()		
}		
for (I=0;i<FocusOffset;i++){		
FOCUS_DESCRIPTOR()		
}		
for (i=0;i<FormOffset;i++){		
FORM_DESCRIPTOR()		
}		
}		

The ID field is used to uniquely identify the page, and is thus used to verify hyperlinks. The Type field contains the page type, as set forth in the following table:

Type	Type code	Delay	Description
Reload	0xFF		Page should be displayed and updated continuously.
Hold	0x00	x	Page should be displayed and not updated continuously until the specified delay has passed.
AutoLink	0x01	x	Page should be displayed and then the link specified by the AUTOLINK element should be executed after the specified delay.

Referring back to the meta-data table, following the Type field and a reserved field, a Delay field is provided which contains a delay measured in seconds (for use with the types

Hold and Autolink). A LinkOffset field indicates the offset of the base of the link table from the start of the meta-data. Similarly, a FocusOffset field indicates the offset of the base of the focus table from the start of the meta-data, and a
5 FormOffset field indicates the offset of the base of the form table from the start of the meta-data.

A page element table is also provided in the meta-data, and comprises a table composed of one or more ELEMENT_DESCRIPTORs. There is an ELEMENT_DESCRIPTOR for every
10 element (e.g., link) on the page. Each element requires additional information based on what type of element it is, and corresponds to some HTML syntax in the source. Some simple rules have been established regarding the structure of the page element table, including the rule that if an "AUTOLINK" element
15 exists, then it is to be the first element in the element array. Also, "FORM" elements are to be located in the first entries of the page element table, after any AUTOLINK element. Form elements are to immediately follow the FORM element for the enclosing form. Lastly, the first element that can receive
20 focus (as specified in the page element table) will receive the initial focus when the page is displayed.

The following table describes the content of an
ELEMENT_DESCRIPTOR.

Syntax	No. of bits	Mnemonic
ELEMENT_DESCRIPTOR(){		
Type	8	Uimsbf
Reserved	8	Uimsbf
LinkOffset	16	Uimsbf
FocusOffset	16	Uimsbf
FormOffset	16	Uimsbf
}		

The "Type" field indicates the type of element, having one
of the values set forth in the table below. The "Type" field
is followed by a reserved field. A LinkOffset field indicates
the offset in bytes, within the link table, of the
LINK_DESCRIPTOR for this element. Similarly, a FocusOffset
field indicates the offset in bytes, within the focus table, of
the FOCUS_DESCRIPTOR for this element. Likewise, the
FormOffset field indicates the offset in bytes, within the form
table, of the FORM_DESCRIPTOR for this element. As can be
appreciated, the size of an ELEMENT_DESCRIPTOR is fixed
regardless of the type of the element.

The following table shows the identifying type code and
the additional information that is required for each type of
element, denoted by an "X":

Element Type	Type code	Focus Specifier	Link Specifier	Form Specifier
FORM	0x00		X	X
AUTOFORM	0x04		X	X
GUIDEFORM	0x08		X	X
INPUT IMAGE	0x0C	X		X
INPUT HIDDEN	0x10			X
INPUT SUBMIT	0x14	X		X
INPUT RESET	0x18	X		X
INPUT CHECK	0x1C	X		X
INPUT RADIO	0x20	X		X
INPUT TEXT	0x24	X		X
INPUT PASSWORD	0x28	X		X
AUTOLINK	0x2C		X	
LINK	0x30	X	X	

To accomplish hyperlinking, the link table contains a LINK_DESCRIPTOR for each page element that is capable of having a hyperlink, as set forth in the following table:

Syntax	No. of bits	Mnemonic
LINK_DESCRIPTOR(){		
ID	16	Uimbsf
ProgramNumber	16	Uimbsf
ProgramElement	8	Uimbsf
PackageNumber	8	Uimbsf
}		

5

The ID field of the link table uniquely identifies the destination page to which an element is linked, and is used to verify hyperlinks. The ProgramNumber field contains the program_number of the program that carries the destination page, and the ProgramElement contains the program element within the program that carries that destination page. An eight-bit reserved field is also present thereafter in the link

10

table. The PackageNumber field represents the level of tiering access, which via an authorization operation, controls the level of service to which the subscriber is entitled. Note that the size of an LINK_DESCRIPTOR is fixed.

- 5 For handling the focus operation, the focus table contains a FOCUS_DESCRIPTOR (list) for each page element that can receive focus. The FOCUS_DESCRIPTOR indicates how to draw focus on the page element. Focus may be indicated with a rectangle, a circle or a polygon as the focus ring. The
- 10 FOCUS_DESCRIPTOR also indicates to which page element the focus should be shifted for each of the direction keys, (i.e., the focus chain). Note that some elements such as hidden text do not receive focus and are not part of the focus descriptor list. The following table describes the content of a

15 FOCUS_DESCRIPTOR:

Syntax	No. of bits	Mnemonic
FOCUS_DESCRIPTOR(){		
ElementUp	16	Uimsbf
ElementDown	16	Uimsbf
ElementRight	16	Uimsbf
ElementLeft	16	Uimsbf
Shape	8	Uimsbf
CoordCount	8	Uimsbf
For (i=0;i<CoordCount;i++){		
COORD_DESCRIPTOR()		
}		
}		

The ElementUp field contains the index within the element table of the element that should next receive focus when the user selects the UP button. For example, in FIG. 6, if focus

is on the "SPORTS REPORT" link 110₂, a logical change in focus for the "UP" button would be to the "TO NEXT PAGE" link 110₁. Thus, the ElementUp field of the focus table for the "SPORTS REPORT" element would contain the index within the element
5 table of the "TO NEXT PAGE" element. However, the ElementUp field of the "TO NEXT PAGE" element may be "TO NEXT PAGE," since no element is above it, or may instead toggle focus back to any of the other elements, depending on the page author's preference as influenced by agreed-upon conventions.

10 Similarly, the ElementDown field contains the index within the element table of the element that should receive focus next when the user selects the Down button, the ElementRight field contains the index within the element table of the element that should next receive focus when the user selects the Right
15 button, and the ElementLeft field contains the index within the Element Table of the element that should receive focus when the user selects the Left button.

The Shape field indicates the shape of the focus ring (drawn by the OSD 96) that will indicate focus on the given element. A 0xFF in this field indicates a polygon, a 0x00 indicates a rectangle, and a 0x01 indicates a circle. The

5 CoordCount field contains the number of coordinates that are needed to define the focus shape, i.e., Rectangle = 2, Circle = 2 and Polygon = N. The following table summarizes the number and type of coordinates supplied for each type of shape:

Shape Name	Shape Code	CoordCount	Description
Polygon	0xFF	N	There are as many coordinates as there are vertices of the polygon. The COORD_DESCRIPTORs are to occur in the order that they would be encountered during a continuous tracing of the polygon edges.
Rectangle	0x00	2	The first coordinate is the upper left corner of the rectangle. The second coordinate is the lower right corner of the rectangle.
Circle	0x01	2	The first coordinate is the center of the circle. The second coordinate is the point on the radius of the circle with the minimum X value.

10 The format of the COORD_DESCRIPTOR is described in the following table:

Syntax	No. of bits	Mnemonic
COORD_DESCRIPTOR(){		
X	16	Uimbsf
Y	16	Uimbsf
}		

The X field contains the X coordinate of a point on the OSD 96, wherein the left-most pixel has an X value of zero and

15 the right-most pixel has an X value of 351. The Y field contains the Y coordinate of a point on the OSD 96 wherein the

top-most pixel has an Y value of zero and the bottom-most pixel has a Y value of 479.

The form table contains a FORM_DESCRIPTOR for each form element. The FORM_DESCRIPTOR contains the NAME/VALUE pair for
5 <INPUT> tags and the ACTION URL for <FORM> tags. Note that the FORM_DESCRIPTOR has a different format for forms that access the Programming Guide, described below. The following table describes the content of a FORM_DESCRIPTOR:

FORM_DESCRIPTOR

Element Type	Coord1	Coord2
INPUT SUBMIT	Button Upper Left	Button Lower Right
INPUT CHECK	Check Upper Left	
INPUT RADIO	Check Upper Left	
INPUT TEXT	TextBox Upper Left	TextBox Lower Right
INPUT PASSWORD	TextBox Upper Left	TextBox Lower Right
INPUT RESET	Button Upper Left	Button Lower Right

The Function field contains the function code for the programming guide function referenced by the GUIDEFORM. The following table shows the encoding used for each of the guide

5 functions:

Function	Function Code
TUNE	0
REC	1
HELO	2
QUIT	3
DATE	4
FROM	5
SUBJ	6
BODY	7
ACKS	8
ACKD	9
ACKB	10

Following a reserved field, the SourceID field contains a unique identifier of a program. The time field contains a Time value, wherein a zero indicates that the time should be treated

10 as the current time.

The COORD_DESCRIPTORs for guide form elements are used to indicate where text should be drawn. The first coordinate specifies the upper left pixel of a region. The second coordinate specifies the lower right pixel of a region.

The COORD_DESCRIPTORs are valid for the DATE, FROM, SUBJ and BODY guide functions.

The NameLength field contains the length of a Name string in ASCII characters, wherein a length of zero indicates that the string is not present. The ValueLength field contains the length of the Value string in ASCII characters, wherein a length of zero indicates that the string is not present. The Name[] field contains the ASCII Name string, if present. For form <INPUT> elements, the Name string contains the string specified by the NAME attribute. For the <FORM> element, the Name string contains the URL string specified by the ACTION attribute.

Similarly, the Value[] field contains the ASCII Value string. For form <INPUT> elements, the Name string contains the string specified by the VALUE attribute. For the <FORM> element, the Value string contains the method string specified by the METHOD attribute.

The following table sets forth the use of the fields within the FORM_DESCRIPTOR for other types of form elements:

Element Type	Coord1	Coord2	Name	Value
FORM			Rvalue(ACTION=)	Rvalue(METHOD=)
AUTOFORM			Rvalue(ACTION=)	Rvalue(METHOD=)
INPUT_IMAGE			Rvalue(NAME=)	Rvalue(VALUE=)
INPUT_HIDDEN			Rvalue(NAME=)	Rvalue(VALUE=)
INPUT_SUBMIT	ButtonUL	ButtonLR	Rvalue(NAME=)	Rvalue(VALUE=)
INPUT_CHECK	CheckUL		Rvalue(NAME=)	Rvalue(VALUE=)
INPUT_RADIO	CheckUL		Rvalue(NAME=)	Rvalue(VALUE=)
INPUT_TEXT	TextBoxUL	TextBoxLR	Rvalue(NAME=)	
INPUT_PASSWORD	TextBoxUL	TextBoxLR	Rvalue(NAME=)	
INPUT_RESET	ButtonUL	ButtonLR		

VI. PAGE AUTHORING

Turning to a consideration of how the page images are
5 generated, FIG. 12 shows the general flow of one such image
from authoring to downloading. First, an author creates a page
using standard HTML content creation tools, such as provided in
an HTML-ready authoring program 150. Such authoring programs
using standard content creation tools are well known and will
10 not be described in detail herein. However, because the pages
are to be viewed on a television, the author should take care
to create an HTML page suitable for television viewing. For
example, the author should select font styles and sizes
appropriate for television display, and avoid color and
15 luminance transitions which generate dot-crawl. Indeed, the
author may wish to view a close approximation of the ultimately
resulting page by using a VGA to NTSC converter with underscan
and antiflicker filtering enabled. In any event, as shown in
FIG. 12, an HTML source 152 including an HTML document and
20 associated image files is provided.

After the author is satisfied with the initial result, the
author runs a Phase 1 post-processing tool 154, which performs
a number of operations on the HTML source 152. Such a tool
includes the operations of rendering the page at a 640 by 480
25 resolution and vertically scaling the page such that the full

640 by 480 image resides within the SMPTE safe action area of a 704 by 480 overscanned television raster (approximately 640 by 432). The scaled page image is bordered by black. In addition, the rendered page is vertically filtered to reduce interlace flicker, and horizontally filtered to reduce cross-luma and chross-chroma interference artifacts.

In phase one processing, the meta-data that define how focus should be drawn on links and form elements are inferred by the HTML layout. The focus geometry is specified on a 352 by 480 grid that overlays the 704 by 480 page image. In other words, only even pixel addresses are allowed in focus specifications. The meta-data that contain the name of the HTML pages associated with each link are inferred from the HTML source 152, as are meta-data that describe any forms. The meta-data defining the focus geometry and link URLs are encoded using standard client-side image map tags, i.e., <AREA>. The HREF attribute for entries relating to form element focus will contain the URL specified by the ACTION attribute in the <FORM> tag. Appended to that URL will be the form query string fragment defined by that form element. The HREF attribute for hyperlinks will contain the URL from the corresponding anchor or imagemap.

The output 156 of this first phase includes a true color bitmap (.BMP) file containing the processed page image and an HTML file that contains the original HTML source encapsulated

in a <META> tag. Also contained are the original image files encapsulated in a <META> tag, a client-side imagemap that is the processed page image, wherein the name of the image file is identical to the name of the HTML source file, and a <MAP> tag
5 defining the geometry of focus for all page elements that can receive focus including form elements. The HTML file also contains the meta-data for the page encapsulated in a <META> tag, and the meta-data for each page element encapsulated in a <META> tag.

10 Since all focus geometry is specified using standard client-side image map syntax, the author can use standard imagemap editing tools to change the focus geometry if desired. Moreover, since the page image is output as a true color .BMP file, the author can make any necessary changes to the image
15 using standard image editing tools. Note that if desired, the anti-flicker, cross-luma, and cross-chroma filtering may be postponed to the next phase (described below).

The order of the <AREA> tags in the <MAP> tag determines the focus chain. As a result, it is possible to edit the Focus
20 Chain for a page at this stage in order to achieve results that cannot be generated simply in the HTML source 152. For example, the author may change the focus chain order by changing the order in which these tags occur, since the first <AREA> tag defines where focus is initially drawn when the page
25 is displayed.

After the author is satisfied with the focus geometry, focus chain order and the final page image, a phase2 post-processing tool 158 is run. The phase2 tool 158 performs a number of operations, including coding the page image as a single MPEG I-Frame, and processing the <MAP> tag to generate focus descriptors for each page element. The focus descriptors for each page element are combined with the other meta-data for each page element.

The output of this second phase is a single HTML file 160 containing a number of items encapsulated in a <META> tag, including the original HTML source, the original image files, the processed page image and the compressed page image. Also contained in the file 160 are the meta-data for the page and the meta-data for each page element therein. After phase2 processing, the page is in the intermediate page format (described above), and the author provides the final file to the carousel building tool 146, such as by running a file transfer program 162 to transfer the file via the Internet 48 to the server 46 of the Information Service.

Note that the phase1 and phase2 processes (154 and 158, respectively) can be run back-to-back without intervention. The break exists therebetween to provide authors the ability to exercise more control over the process if so desired. Thus, as described above, between phase1 154 and phase2 158 of the tool chain, an author may edit the focus geometry by using any

number of existing imagemap editing tools, while the focus chain may also be edited by editing the FOCUS meta-data.

To allow the HTML author to reference user-specific data stored in the set-top-box 28 and perform other limited functions, a set of form element names are defined to have special meanings, as set forth in the table below:

Element name	Meaning and usage	Format
_SHIPNAME	Default shipping name. May be used for transactions and bingo card.	
SHIPSTREET		
SHIPCITY		
SHIPSTATE		
SHIPZIP		
_CARDNAME	Default cardholder name. May be used for one-button purchase.	
CARDTYPE		
CARDMONTH		
CARDYEAR		
_EMAIL	Default Email address for this box.	Standard RFC822 address syntax.
TIME	Current time.	
_QUANTITY	Name to use for quantity input on transaction form in order to enable TOTAL.	
_PRICE	Name to use for price hidden text on transaction form in order to enable TOTAL	
_SANDH	Name to use for shipping and handling etc hidden text on transaction form if needed for TOTAL	
_TOTAL	Causes the Browser 62 to evaluate the following expression that can be placed in a read-only text entry element. TOTAL = QUANTITY * PRICE + SANDH	

When included in the body of a form as hidden text, these elements generate a standard name/value pair in the form query string. For example, the tag <INPUT TYPE=HIDDEN NAME="_EMAIL">

will generate the following sub-string in the form query
string: "&_EMAIL=set_top_box_name@customers.tci.com"

VII. OTHER

5 At least some existing programming guide applications and
cable system infrastructures support one-way e-mail broadcasts
to all users. This function can be extended to allow one-way
e-mail to a specific subscriber, using the existing (e.g.
PreVue) e-mail notification and display mechanism. E-mail data
10 can be sent to a specific set-top box via the out-of-band
modulator 60 (FIG.2) and the out-of-band tuner 71 (FIG.3), in
the same manner that a specific box is enabled for receiving a
pay-per-view movie. Although not directly linked to the
Information Service architecture, a head-end e-mail server is
15 considered a part of the Information Service head-end
installation, and the e-mail server software is supplied by the
assignee of the present invention.

The Information Service e-mail client is implemented using
standard HTML forms. A simple example would be a form
20 containing buttons for "Previous", "Next", and "Delete" which
would submit the appropriate query strings to the guide in
order to have the mail text rendered using the OSD 96 over the
page image. The author of the page can specify where the
"From" address is rendered and where the message text is
25 rendered. The coordinates for these fields are referenced to a

352 by 480 OSD grid, where the original 640 by 480 page image underlays the center 320 by 432 pixels.

Although at present e-mail is generally read-only, it is understood that two-way e-mail is feasible. For example,

5 outgoing e-mail messages may be written to the memory 82 and polled via the modem 134 (FIG. 3) by an e-mail server or the like, or sent directly (or as soon as a telephone line is available) thereto via the modem 134 upon user command.

Moreover, a backchannel which sends information on the
10 transmission medium 24 from the various set-top boxes back to the head-end 22 may be dedicated, in which event all data, including form entry data and e-mail data, can be immediately transferred without polling the modem 134. However, in order for e-mail to be practical, a more sophisticated alphanumeric
15 input device, such as a conventional QWERTY keyboard arranged for communicating with the set-top box, would likely need to be provided.

It is also feasible to add audio to the carousel 50, whereby audio may be optionally played while the user is in the
20 Information Service. In such a system, part of the information sent with each transmitted page is the next block (or blocks, if multiple, user-selectable audio streams are transmitted) of encoded audio data. Depending on the amount of memory in the set-top box, the audio data may be buffered so as to load more
25 than one carousel revolution's worth (e.g. eight seconds) of

audio data from a given carousel 50 into the set-top box 28 for each stream. However, by regularly changing the carousel, the audio may be a real-time broadcast.

Lastly, instead of a carousel 50, it is feasible to have
5 the server 46 execute a program that selectively injects the pages into the transport stream. For example, based on statistical information such as page popularity in conjunction with the time of day, (information which may be sampled and polled from the set-top box 28), more popular pages can be
10 injected more frequently into the stream than less popular pages. The maximum latency for a given page can thus be controlled, without effecting the total number of pages possible, (which occurs with a carousel by increasing a page's frequency in the carousel at the expense of decreasing the
15 number of distinct pages therein).

As can be seen from the foregoing detailed description, there is provided an interactive entertainment and information system using a cable television set-top box, wherein existing digital set top boxes may be used without need for modification
20 of the hardware therein. The system enables a user to hyperlink between pages of information, and facilitates an interactive relationship between transmitted programming and information pages related thereto. The user may submit form information, including forms related to a viewed television

program. The system provides a simple to operate, low cost information service, while being flexible and extensible.

While the invention is susceptible to various modifications and alternative constructions, a certain

5 illustrated embodiment thereof is shown in the drawings and has been described above in detail. It should be understood, however, that there is no intention to limit the invention to the specific form disclosed, but on the contrary, the intention is to cover all modifications, alternative constructions, and

10 equivalents falling within the spirit and scope of the invention.